



Course : B.Tech (ECE)
Class Nbrs : VL2023240501354, 1338, 1343, 1345, 1348, 1352, 3749,
Slot : C2+TC2
Date : 3rd April 2024
Course Type : ETH
Course Mode: CBL
Marks : 50
Duration : 90 Min
Faculty: RAMACHANDRA REDDYS KALAIVANI, ABHIJIT BHOWMICK, SUDHAKAR M S, LAVANYA N,
SARANYA K.C, ANANTHAKRISHNA CHINTANPALLI.

Each Question carries 10 marks

Q.No	Question	Marks
1.	<p>Design a band-stop Butterworth filter that satisfies the following magnitude response specifications.</p>	10
2.	<p>Obtain an analog Chebyshev filter transfer function that satisfies the constraints:</p> $0.707 \leq H(j\Omega) \leq 1, \quad 0 \leq \Omega \leq 2;$ $ H(j\Omega) \leq 0.1, \quad \Omega \geq 4$	10
3.	<p>Using the bilinear transformation approach with $T = 1$ sec, find the system function $H(s)$ of the lowest order Butterworth filter for the following specifications:</p> <p>3dB ripple in pass band $0 \leq \omega \leq 0.2\pi$ 25dB attenuation in stop band $0.45\pi \leq \omega \leq \pi$</p>	10
4.	<p>Given a transfer function,</p> $H(s) = \frac{2}{(s + 0.5)^2 + 4}$ <p>Use impulse invariant technique to convert that into digital filter $H(z)$, using sampling interval of 1 sec. And also locate the poles and zeros of $H(z)$ in the z - plane.</p>	10
5.	<p>Realize the given $H(z)$ as cascade form of two second order transfer functions:</p> $H(z) = 1 + \frac{3}{2}z^{-1} + \frac{5}{4}z^{-2} + \frac{1}{2}z^{-3} + \frac{1}{8}z^{-4}$ <p>Additionally, compute the difference equation for each of the stages.</p>	10

